

IP Camera Client CMS

Install Software

["IPCC.exe"](#) can be downloaded from our Website under User Manuals

Camera must already be connected to your router by WiFi, please use your smart phone to setup the camera to your router. If you do not own a smart phone, refer to pc-install manual:

The camera(s) can be added and viewed only from a local network)

Adding the camera

- **Do not reset the camera** if the camera is already has been setup with your smart phone. You are simply adding the camera to the PC.
- When you install the software and run, it will ask you for the PW. This is NOT the camera PW. This PW refers to the software PW and there is no PW as default. Just leave it blank and continue.
- Hit "CONFIG" icon (gear) on the top and chose "Device Management"
- Add Area first (you can name it anyways)
- Hit "search". If your camera comes up in the column, choose it and hit the ">>" button right above the "search" button. *(If no camera is found, your PC may not be connected to the same network as the camera. Sometimes, if your PC is connected via CAT-5,6 cable, may not find the camera. Please install a wireless adapter to your PC and try again.)*

Viewing the camera

- Hit "PREVIEW" icon (camera)
- Double click on the UID on the left column. "Channel 01" will be displayed right below, double click the "Channel 01".
- Watch the status below, the camera image should pop up right away. *(If "connect failure" this is 99% due to the wrong PW, please go back to configuration → click on the camera ip address → modify device and change to the correct PW. Remember, there is only ONE PW for the camera and must be the same for all the devices.)*

Preparing for Recording

- Hit "CONFIG" icon and select "Record Management"
- Check the checkbox for "enable the plan of record" and hit "Save" (right, below the chart)
- Check the checkbox for c:\ and hit "Save" (all the way below)

Continuous Recording

- On the Preview screen, right click on the video and choose "record" Green film icon on the right/top of the quadrant will be lit. If not, make sure checkbox for c:\ is checked and saved.
- To stop, simply right click again and choose "record" again.

Schedule Recording

- Hit "CONFIG" icon and select "Record Management"
- Click on the camera UID and check the "Enable the plan of record" box ON.
- Choose the time on the chart you wish schedule and record. (Click and hold one of the cell in the time chart and drag. Cells will turn green as you do so. Do the same to the green cells to undo).
- Hit "save" (right below the chart) after appropriate calls are selected for recording.
- Go back to "preview", when the camera is recording by schedule, the film icon will turn blue.

Motion Recording

- Hit "CONFIG" icon and select "Linkage Alarm"
- Double click on the camera UID and its channel, check the "Enable the Linkage Alarm" and "Linkage Record" boxes ON.
- Choose the time on the chart you wish to detect motion and record. (Click and hold one of the cell in the time chart and drag. Cells will turn green as you do so. Do the same to the green cells to undo).
- Check the "Linkage Record" box ON.
- Go back to "preview", when the camera is recording by motion, the film & alarm icon will turn RED.
- Upon motion, the camera will record as long as there is motion.
- If the motion detection set-up is correctly set-up, when motion occurs, both the red alarm icon and green film icon will be lit on the viewing screen.

The alarm icon does not lit up RED?

The motion trigger may have been turned OFF with another device. Please use your smart phone app to set the motion recording ON.

Notes:

You can use multiple of above recording methods simultaneously.

Playback....

This manual is still in progress; but the rest is self explanatory. Just hit the playback button, you will know how to use it.